

A3500EDI INVERTER GENERATOR



Image for illustration purpose only

Starting Power	3200W
Rated Power	3000W
Noise Level	58dB
Frequency	50/60Hz

AiPower A3500EDI inverter generator provides clean, quiet 3,200 starting watts and 3,000 running watts. It is great for your outdoor events such as concerts, camping trips, tailgating parties, racetracks, RVs, and more. At only 28kgs, you can take portable power wherever you go. At 58dBA @ %50 Load at 7m, you are assured quiet operation. The generator features a 3-in-1 intelligent digital meter, which indicates the data of voltage, run hours, frequency, power level, fuel level, output indicator, overload alarm, and low oil alert.



SPECIFICATION

MODEL	A3500EDI
Max Starting Power	3.2 KW / 4.2 kVA
Running Power	3.0 KW / 3.7 kVA
AC Load (Volts)	230
Phase, Frequency	Single, 50/60Hz
Rated Amperage	13.0A
Starting Method	Manual / Remote
Engine Type	Gasoline
Engine Model/CC/Hp	SH150B/149cc/5.5HP
Noise Level	58dB
Fuel Tank Capacity	6.0L
Run Time-50 %Load	6.0Hrs
Run Time-100 %Load	3.5Hrs
Fuel Consumption	1.0L/Hr (50 %Load)
Engine Oil Capacity	0.48L
Digital Display	3-in-1 Meter
Eco-Throttle	✓
Socket	1x16A
THD	<%3
Battery	4AH
Wheel	2.7in
Net / Gross Weight	28 / 30Kg
Product Dimension(LxWxH)	570x395x520mm

FEATURES

- Ultra Quiet : 58dB
- Digital inverter technology
- Safe Clean Power
- Economy mode to save fuel
- Overload protection
- Intelligent 3-in-1 Volt Meter
- Versatile for Powering Worldwide Electronics

GREAT CHOICE FOR:

